

# DVR PTZ KEYBOARD CONTROLLER

## PTZ735



Control All Your PTZ Camera Functions With The PTZ735



### Features

- ✓ Control Up To 255 PTZs
- ✓ 14 Different Protocols
- ✓ Password Protection
- ✓ Connect Up To 15 Auxiliary Keyboard
- ✓ 8 Programmable Buttons
- ✓ Surge Protection

### Description

The PTZ735 keyboard controller can control all of our PTZ cameras. The PTZ735 can be used for all the functions usually controlled by the DVR. With the PTZ735 you can control a maximum of 255 x PTZ domes with a maximum communication distance of up to 1.2 km. The PTZ735 is very easy to operate and control all the features of connected PTZ cameras such as pan, tilt, zoom etc. The PTZ735 has 8 programmable buttons giving quick access to 8 commonly used functions.

#### Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright

# DVR PTZ KEYBOARD CONTROLLER

## PTZ735



### Controls

- \* All operations are displayed in the LCD display.
- \* One PTZ735 can control up to 255 x PTZs.
- \* The address range for PTZ domes is 0 ~ 254.
- \* Up to 15 x auxiliary keyboards can be connected in range 0 ~ 15.
- \* Up to 14 different protocols and different baud rates can be selected as configuration is set by the LCD display.

Supports Protocols: Pelco-D, HIK, SAMSUN, RULE, ALEC, YANN, B01, NCS850, CS850, Pelco-P.

Baud Rates Provided: 1200, 2400, 4800, 9600, 19200.

### Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright

# DVR PTZ KEYBOARD CONTROLLER

## PTZ735



### Specifications

---

|                                  |                              |
|----------------------------------|------------------------------|
| Input Voltage . . . . .          | 12V DC                       |
| Current Consumption . . . . .    | 80mA                         |
| Protocol . . . . .               | Pelco D & P                  |
| Other Protocols . . . . .        | 12 others                    |
| Cabling . . . . .                | Max Length 1200 Meters       |
| Maximum Number Of PTZs . . . . . | 255                          |
| Joystick . . . . .               | 3D                           |
| LCD Screen . . . . .             | Yes                          |
| Dimensions . . . . .             | (L) 320 x (W) 180 x (H) 61mm |

#### Disclaimer

The technical specifications contained are given in good faith as being accurate but due to a continued program of improvement may change from time to time without notice. We apologise for any inconvenience due to changes of specification or errors and omissions within this document. Copyright